



Creative
 CT6670
 2198
 DDC REV A00
 SDZ-MODS.COM

PARTS	VALUE	PACKAGE	QTY	Note
R163	DNP	0603	1	
R110	10kR	0603	1	
R107, R109	1kR	0603	2	
R113, R114, R115, R127, R128, R129, R130, R131, R132, R133, R134, R135, R136, R137, R138, R139, R140, R149, R150, R151, R152	22R	0603	21	
R103, R105, R106, R108	4.7kR	0603	4	
RA38, RA39, RA40, RA41, RA42	22R	0603	5	
R141	47R	0603	1	
C152, C153, C154, C155, C156, C157, C159, C160, C161, C162, C163, C164, C165, C166	100pF 50V C0G	0603	14	
C47, C50, C51, C53, C54, C59, C61, C64, C66, C67, C81, C84, C89, C93, C95, C105, C108, C110, C111, C112, C117, C120, C124, C130, C151	1nF 25V X7R	0603	25	
C21, C41, C46, C52, C56, C57, C58, C60, C62, C63, C65, C68, C69, C70, C71, C72, C73, C74, C75, C76, C77, C78, C79, C80, C82, C83, C85, C86, C87, C88, C90, C91, C92, C94, C96, C97, C98, C99, C100, C101, C102, C103, C104, C106, C107, C109, C113, C114, C115, C116, C118, C119, C121, C122, C123, C125, C126, C127, C128, C129	100nF 25V X7R	0603	60	
C9, C28, C145, C146, C147, C148, C149, C150	4.7uF 6.3V X7R	1206	8	*1
U19, U20, U21, U22, U23, U24, U25, U26, U27, U28, U29, U30	VT514264-25	S0440		*2

Note 1. Can be replaced with higher value/higher voltage.
 Note 2. Can be replaced with V53C16258HK22 V53C16258HK25 VT514264-25 M11B416256A-25J SM01C256K16CJ-25 etc.